

Digital multimeter

Model: CD731A

Features:

- 1- 3-3/4 digits 3200 count
- 2- AC + DC true RMS (CD751 only)
- 3- Wide current measurement function
- 4- Auto/manual measurement with current rang
- 5- Auto power save (CD751
- 6- Auto power off (CD731/CD721)
- 7- W52 x H26.5m
- 8- Large LC
- 9- Safety cover for the terminal for large current
- 10- Holster (for wall hanging and fixing test leads)
- 11- Tilt stand



Standard Accessories Included

- Test leads (TL-21) x 1set
- Holster (H-70) x 1

Specifications:

Function	Measuring range	Best accuracy	Resolution	Input impedance
DCV	320m/3.2/32/320/1000V	± (0.5%+2)	0.1mV	DCV: 10M~ 100MΩ
ACV	3.2/32/320/750V	± (1.2%+5)	0.001V	
DCA	32μ/320μ/3200μ/32m/320m/20A	± (1.4%+2)	0.01μA	ACV: 10M~ 100MΩ
ACA	32μ/320μ/3200μ/32m/320m/20A	± (1.8%+5)	0.01μA	
Resistance	320/3.2k/32k/320k/3.2M/30MΩ	± (1.2%+2)	0.1Ω	
Continuity	Buzzer sounds at approx. 20Ω. Open voltage : approx. 1.3V			
Diode test	Open voltage : approx. 3V			
Bandwidth	40~400Hz			
Fuse / Battery	0.5A/250V IR 300A φ5.2×20mm 20A/250V IR 1000A ceramic	R6P×2		
Size / Weight	H165.5×W78×D41.5mm/approx. 315g (including holster)			
Standard accessories included	Test lead (TL-21) , Holster (H-70) , Instruction manual			