

MULTIFUNCTIONAL ENERGY METER

Model: WF-D02B



Description:

Energy monitor measures Voltage, Watt, kWh, \$, Amps, power factor and time; CE and RoHS approved.

Functions:

1. Measure real-time voltage of the power supply (90~150V AC or 160~280V AC);
2. Measure real-time operation power of the appliances (0~3000W);
3. Show the power consumption (0~9999kWh);
4. Calculate the cost of energy according to the pre-set price of energy (0~\$9999); price of energy can be pre-set to the local price by users;
5. Operation condition monitor: The indicator light will flicker when the real-time ratio of operation condition reaches its alarm point.
Ratio of operation condition is the ratio between accumulated operation time per hour (running power is over preset standby power) and 1 hour.
Alarm point for ratio of operation condition and standby power can be pre- set.

6. Show the operation time of appliances (0~24h~9999d)

7. Measure real-time current: 0~15A

8. Measure Power Factor: 0~100%

Parameters:

1. Voltage: 90~150V AC or 160~280V AC; 50/60 Hz;

2. Peak load: 15A

3. Temperature: -10~60 C

4. Humidity: 10~95% RH

Made in china