

Digital multimeter

Model: CD721



Description:

- 1- 3-3/4 digits 3200 count
- 2- Wide current measurement function
- 3- Auto/manual measurement with current range
- 4- Auto power off
- 5- W52 x H26.5mm
- 6- Large LCD
- 7- Safety cover for the terminal for large current
- 8- Holster (for wall hanging and fixing test leads)
- 9- Tilt stand

Specifications:

Function	Measuring range	Best accuracy	Resolution	Input impedance
DCV	320m/3.2/32/320/1000V	± (0.5%+2)	0.1mV	DCV: 10M~ 100MΩ
ACV	3.2/32/320/750V	± (1.2%+5)	0.001V	
DCA	32m/320m/12A	± (1.4%+2)	0.01μA	ACV: 10M~ 100MΩ
ACA	32m/320m/12A	± (1.8%+5)	0.01μA	
Resistance	320/3.2k/32k/320k/3.2M/30MΩ	± (1.2%+2)	0.1Ω	
Continuity	Buzzer sounds at approx. 20Ω. Open voltage : approx. 1.3V			
Diode test	Open voltage : approx. 3V			
Bandwidth	40~400Hz			
Fuse / Battery	0.5A/250V IR 300A φ5.2×20mm 12A/250V IR 500A	R6P×2		
Size / Weight	H165.5×W78×D41.5mm/approx. 315g (including holster) , approx. 220g (CD721NH)			
Standard accessories included	Test lead (TL-21) , Holster for CD721 (H-70) , Instruction manual ※No holster with CD721NH			