

Digital Multimeter Pro'sKit MT-1210



PRO'SKIT MT-1210 DIGITAL MULTIMETER FEATURES

- Low battery indication
- 3½ digit (1999) LCD
- 1.0% best accuracy
- Functions:
 - - DC current
 - - AC/DC voltage
 - -resistance
 - continuity (with buzzer)
 - diode test
 - transistor test
 - 1.5V battery test
- Backlight
- Manual ranging
- Data hold function

PRO'SKIT MT-1210 DIGITAL MULTIMETER TECHNICAL SPECIFICATIONS

Display	3½ digit (1999) LCD
DC voltage, V	200mV $\pm(1.0\%+2d)$ 2V/20V/200V $\pm(1.0\%+2d)$ 500V $\pm(1.2\%+5d)$
AC voltage, V	200V $\pm(2.5\%+10d)$ 500V $\pm(2.5\%+10d)$
DC current, A	200μA $\pm(2.0\%+5d)$ 2mA/20mA/200mA $\pm(2.0\%+5d)$ 10A $\pm(3.0\%+5d)$
Resistance, Ω	200Ω $\pm(1.0\%+5d)$ 2kΩ/20kΩ/200kΩ $\pm(1.0\%+5d)$ 2MΩ $\pm(1.5\%+5d)$
Special Function	1.5V battery and transistor tests
Battery	NEDA 1604 or 6F22 9V (not included)
Size (D × W × H), mm	144 × 70 × 32
Weight, g	175