

Mini current transformer

CT102



Features

- 1- High accuracy, AC measurement accuracy up to class 1.0;
- 2- Small phase error, typical phase shift is at 1-10'; Additional compensation not needed;
- 3- Good isolation from Primary to Secondary;
- 4- Very reliable and stable performance at different temperature conditions;
- 5- Frequency: 50Hz/60Hz Ambient Temperature: -40°C ~ 70°C;

Specifications:

Measurement Current		80A
Ratio	Current	80A/40mA
	Turns	1:2000
Load		12.5Ω
Insulation voltage		3000V
Phase error		<15'
Accuracy Class		0.1

Made in china