

AUTO AV MATRIX 8x8 + REMOTE

Model: 5548



Model Number	SB-5548
Video Inputs	8×Composite Video, 75Ω on RCA Connectors
Audio Inputs	8×Stereo R/L, 47KΩ on RCA Connectors
Video Outputs	8×Composite Video, 75Ω on RCA Connectors
Audio Outputs	8×Stereo R/L, 47KΩ on RCA Connectors
Video Bandwidth	>150MHz
Video Distortion	<1.2db(Standard +/- 3db)
Audio Distortion	<0.6db (Standard +/- 3db)
Channel Isolation	>50db
S/N Ratio	>50db
Video Crosstalk	>60db
Control Method	Front Panel Switches and IR Remote Control Unit
Power Consumed	1A Maximum
Power Source	+12 Volts DC (- out , + in)
Dimensions (H,W,D)	1.8×12×7.1 (45×304×180mm)
Net Weight (Unit Only)	2.2 lbs.(1Kg) Approx.

Applications:

1. DVDs
2. VCRs
3. VCDs
4. STBs
5. Game Consoles
6. Satellite Receivers

Operation of the Matrix Routing Switcher

There are four pushbuttons on the front panel. The first selects which of the 8 inputs is routed to Output 1, the second button selects which input is routed to Output 1, the second button selects which input is routed to Output 2, etc. Simply choose the button corresponding to the output you want to change and press it repeatedly to toggle through AV Inputs 1 thru 8.

The front panel LEDs indicates which input is connected to its respective output at any given time. The IR Remote Control has a separate row of four buttons for each of the outputs. Each of this buttons corresponds to one of the eight inputs. Simply press the appropriate button to select the desired input.

Made in Taiwan