

100W POWER INVERTER



SPECIFICATIONS:

1. Max Output Power:100W, Continuous Output Power: 70W.
2. With the multiple protection circuit, it would do no harm to the equipment and automobile.
3. Special versatile socket, suitable for various kinds of plugs.

OPERATION GUIDE:

1. Insert the front part of this product into the cigar lighter socket of the automobile.
2. Make sure that the power indicator light is on.
3. Insert the power plug of your electrical appliance into the socket of this product.
4. Please pull out this product from the cigar lighter socket when you do not use this product.

TECHNICAL PARAMETER:

Input voltage range	DC 10V-15V				
Output voltage range	AC :	110V	220V	230V	240V
Max. Output Power	100W				
Continuous Output Power	70W				
Over voltage shutdown	DC 14.5V-15.5V				
Low voltage shutdown	DC 9.5V-10.5V				