

INVERTER 150W

Model:SP-150

Useful Applications:

Run Notebook Computers, Radios, Small TVs, VCRs, Lamps, Fans, Fax, ...etc.

Specifications:

- *Input Voltage Range: DC 10~15V (12V) // DC 20~30V (24)
- *Input Full Load Current: 15A (12V) // 8A (24V)
- *Standby Input Current: <0.28A (12V) // <0.18A (24V)
- *Output Voltage (AC): 220V~240V
- *Output Waveform: Modify Sine wave
- *Output Frequency: 50Hz
- *Continue Output Power: 150W
- *Peak Output Power: 450W
- *Efficiency: 90%
- *Battery Low Pre-alarm: $10.5 \pm 0.5V$ (12V) // $21 \pm 0.5V$ (24V)
- *Battery Low Shutdown: $10 \pm 0.5V$ (12V) // $20 \pm 0.5V$ (24V)
- *Thermal Protect: $60 \pm 5^{\circ}C$ (Microcontroller)
- *Auto-operation Fan (Temperature or Load)
- *Overload Protect: Yes (Microcontroller)
- *Output Short Protect: Yes (Microcontroller)
- *Battery Ex. 12V / 24V Protect: Yes (Microcontroller)
- *Battery Polarity Protect: Yes (By Fuse)
- *Fuse: 15A*1PC (12V) // 10A*1PC (24V)
- *Dimension (L*W*H) mm: 120*73*45
- *Weight: 480g



Made in Taiwan