



Digital Power Supply (30V - 20A) Model: HY3020



This power supply is a kind of high-steady multiple DC power supply and its out put voltage and restricted current can be adjusted continuously; voltage and current can be transformed automatically as well. HY3020 is LED Display.

Output Voltage: 0-30V

Output Current: 0-20A

Specifications:

Input Voltage	220/110V AC $\pm 10\%$ 50Hz/60Hz $\pm 2\text{Hz}$
Power Effect	CV< = 0.02% +3mV; CC< = 0.5% +3mA
Overload Effect	CV< = 0.03% +10mV (I>6A); CC< = 0.5% +10mA (I>6A)
Waves and Noises	CV< 3mVr.m.s CC< 10mAr.m.s
Protection	Current restricted and short-circuit protection
Voltage indication accuracy	LED $\pm 1\%$ + 2digits
Current indication accuracy	LED $\pm 1\%$ + 2digits
Operational temperature	0 ~ +40 C°
Relative Humidity	<90%

Made in China