

Bench-Top Digital Multimeter Model: GDM-8034

Description:

large 0.5" LCD with 3 1/2 digits always provides a crisp display of the measurement results. A series of powerful built-in functions, such as AC/DC Voltage, AC/DC Current, Resistance, Capacitance, Diode Test, and an Audible Continuity Beeper, makes application measurements simpler and easier. A compact profile, sufficient functionality, and excellent cost to performance make the GDM-8034 best suited for educational institutions such as schools and training centers.

Features:

- 8 Functions AC/DC Voltage, AC/DC Current, Resistance, Capacitance, Diode Test and Audible Continuity Beeper
- High Voltage 1000V and 20A Current Range
- 0.5% Basic DCV Accuracy
- LCD Display



Specifications:

DC Voltage Range		200mV, 2V, 20V, 200V, 1000V 5 ranges
AC Voltage Range		200mV, 2V, 20V, 200V, 750V 5 ranges
DC Current Range		200μA, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
AC Current Range		200μA, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Resistance Range		200Ω, 2kΩ, 20kΩ, 200kΩ, 2MΩ, 20MΩ 6 ranges
Capacitance Range		2nF, 20nF, 200nF, 2μF, 20μF 5 ranges
Diode Test	Test Current	Max. 2.5mA
	Open Voltage	Max. 3.2V
Continuity Beeper	Description	Buzzer sounds when conductance < 30Ω
	Test Current	Max. 2.5mA
	Open Voltage	Max. 3.2V
Display		0.5" LCD display
Power Source		AC 110V/220V ±15%, 50/60Hz
Accessories		User manual × 1
		Power cord × 1
		Test lead GTL-107A × 1
Dimensions & Weight		245(W) × 95(H) × 280(D) mm Approx. 2kg