

Digital Earth Meter Model: PDR-200DG



Features:

- Simple 2 ranges 200 / 2000 Ω
- Simple operation with push button
- Phase detection system used for circuit for stable measurement
- Easy self calibration
- Low power indication AC 30V range to avoid indication errors caused by leak current

Specifications:

Earth resistance measuring range	200/2000 Ω Resolution 0.1/1 Ω Accuracy $\pm (3\%+5)$
Earth AC voltage measuring range	0~30V Resolution : 0.1V Accuracy $\pm (3\%+5)$
Display	LCD Max. 1999 with overrange indication
Operation	Constant current system (tripolar or bipolar)
Battery	R6PX6
Size / Weight	W163×H100×D47mm/470g
Standard accessories included	Carrying case for PDR-200DG (C-PDR200), Earth bar set (SET-PDR201), Carrying bag for PDR-200DG and accessories (C-PDRCB), Instruction manual