



Pocket size digital multimeter

Model: PM11

Features:

- 1- 3-3/4 digits 4000 count
- 2- Compact size test leads affixed to the body
- 3- Auto power off
- 4- Full auto range arc. bar graph
- 5- Probes can be snapped into a fixed position atop the case.



Specifications:

Function	Measuring Range	Best Accuracy	Resolution
DCV	400m/4/40/400/500V	±(0.8%+4)	0.1mV
ACV	4.0/40/400/500V	± (2.3%+8)	0.001V
Resistance	400/4.0k/40k/400k/4.0M/40MΩ	± (2.0%+4)	0.1Ω
Continuity	Buzzer sound at less than 20Ω open voltage: approx 1.3V		
Diode test	Open Voltage : approx. 3V		
Bandwidth	45~1KHz		
Battery	Button battery LR-44X2		
Size/Weight	H117XW76XD18mm / approx 117g		
Standard Accessories Included	Instruction Manual		

Made in Japan