



NB201

INTELLIGENT ONE SWITCH METER

- Pocket size, 2000 counts LCD display with unit annunciators, ideal for DIY hobbyist
- Auto Selection: **detects AC voltage, DC voltage and resistance automatically**
- Audible continuity check
- Data hold and LCD backlit
- Auto /manual ranging, auto power off
- Safety as per IEC1010-1 CAT.II 600V

Technical specifications

DCV: 2/20/200/600V ($10M\Omega$), $\pm 0.5\%$

ACV: 2/20/200/600V ($10M\Omega$, 50~400Hz), $\pm 0.8\%$

OHM: 200/2k/20k/200k/2M/20M Ω , $\pm 0.5\%$

Continuity buzzer ($<60\Omega$) & diode test

Battery: 1.5Vx2, AA/UM3/R6P

Dimensions: 148x78x42mm

Weight: approx. 280g

Accessories: holster

REF: 01N201X0000

☒ CE (EMC), ☐ UL, ☐ CE (LVD)

Sinometer